## PRODUCT SPECIFICATION

**COSMO**ELECTRONICS CORPORATION


SOLID STATE RELAY:


KSD215AC3

NO. 58032215 SHEET 1 OF 3


REV.

1. OUTSIDE DIMENSION: UNIT ( mm )





#### 2. SCHEMATIC: TOP VIEW



# **PRODUCT SPECIFICATION**

	cosmo	SOLID STATE RELAY:			
		LODO4E A OC			
	ELECTRONICS CORPORATION	KSD215AC3			

NO. 58032215 SHEET 2 OF 3

REV.

3. Absolute Maximum Ratings

(Ta=25°ℂ)

( /
Unit
VDC
VDC
Arms
Α
V
Hz
A/us
Vrms AC
Vrms
$^{\circ}\!\mathbb{C}$
$^{\circ}\!\mathbb{C}$
$^{\circ}\!\mathbb{C}$

#### 4. Electrical Characteristics

(Ta=25°ℂ)

Parameter		Symbol	Conditions	MIN	TYP	MAX	Unit
lmm.ut	Pick-up voltage	$V_{pu}$	It=1Arms			4	VDC
Input	Input current	l <sub>in</sub>	Vin=5~12V	5		35	mA
	On-state voltage	$V_{T}$	I <sub>⊤</sub> =1Arms			1.5	Vrms
	Operating current	l <sub>op</sub>	Vout=240vrms	50			mArms
	Leakage current	I <sub>leak</sub>	Vout=240vrms			7	mArms
Output	Critical rate of rise of	dv/dt		50	200		V/us
	off-state voltage						
	Zero-cross voltage	V <sub>ox</sub>			YES		
	Load Voltage Rating	$V_{\text{out}}$	I <sub>T</sub> =50mArms MIN	50		280	VAC
Minimum trigger current		I <sub>FT</sub>	V <sub>DRM</sub> =600V			25	mA
Isolation resistance input to output		R <sub>ISO</sub>	DC500V	10			GΩ
Turn-on time		T <sub>on</sub>	60Hz AC			8.3	mS
Turn-off time		T <sub>off</sub>	60Hz AC			8.3	mS
Thermal resistance		R <sub>th</sub>					
(between junction and case)		(j-c)l			1.3		°C/W

### PRODUCT SPECIFICATION

# COSMO ELECTRONICS CORPORATION

SOLID STATE RELAY : KSD215AC3

NO. 58032215 REV. SHEET 3 OF 3

#### Application Notice

The statements regarding the suitability of products for certain types of applications are based on cosmo's knowledge of general applications of cosmo products. Such statements are not binding statements about the suitability of products for a particular application. It is the customer's responsibility to verify the specifications are suitable for use in a particular application. Customers are solely responsible for all aspects of their own product design or applications. The parameters provided in the datasheet may vary in different applications and performance may vary over time. All operating parameters (including typical parameters) must be validated by customer's technical experts for different applications. cosmo assumes no liability for customer' product design or applications. Product specifications do not expand or otherwise change cosmo's terms and conditions of purchase, including but not limited to the warranty expressed therein.

When using cosmo products, please comply with safety standards and instructions. cosmo has no liability and responsibility to the damage caused by improper use of the instructions specified in the specifications.

cosmo products are designed for use in general electronic equipment such as telecommunications, office automation equipments, personal computers, test and measurement equipments, consumer electronics, industrial control, instrumentation, audio, video.

cosmo devices shall not be used in equipment that requires higher level of reliability and safety, such as nuclear power control equipment, telecommunication equipment(trunk lines), space application, medical and other life supporting equipments, and equipment for aircraft, military, automotive or any other application that can cause human injury or death.

cosmo reserves the right to change the specifications, data, characteristics, structure, materials and other contents at any time without notice. Please contact cosmo to obtain the latest specification.

cosmo disclaim any and all liability for any errors, inaccuracies or incompleteness contained in any datasheet or in any other disclosure relating to any product.